



			VR3.3-	40	100	200
ITEM	PART #	MATERIAL	QTY	QTY	QTY	
c	9371	Bolt, Machine 1/2" x Req'd Length	2	2	2	
d	9863	Washer, Round 1-1/4" X 9/16"	2	2	2	
p		Connector, As Req'd				
p1	9027	Crimpet, #6-#6 Cu	1	1	1	
av	3114	Wire, Insulated Tap - #2 AWG	30'	30'	30'	
av1	3110	Wire, #2 Jacketed Strd.	4'	4'	4'	
ap	2140	Clamp, Hotline	3	3	3	
ap1	2147	Stirrup, Hotline	3	3	3	
be	640040-01	Recloser, Cutout Mount - 40 Amp	3			

			VR3.3-	40	100	200
ITEM	PART #	MATERIAL	QTY	QTY	QTY	
be	640100-01	Recloser, Cutout Mount - 100 Amp			3	
be	640200-01	Recloser, Cutout Mount - 200 Amp				3
cj	3010	Wire, #6 Cu Bare	1'	1'	1'	
ek	9094	Locknut, 1/2"	2	2	2	
gc	8240-1	Conduit, 1" PVC	20'	20'	20'	
rp	4725	Cover, Cutout	3	3	3	
	9160-1	Straps, 1"	5	5	5	
1		Recloser Controller	1	1	1	
2		Cable, Controller Power	1	1	1	

NOTE

1. Mount cutouts so Recloser faces the climbing face of pole.
2. Where source wire is 336.4 ACSR (18/1)), replace item ap1 with part no. 2148 - Hot Line Stirrup 336.
3. For poles greater than 45 ft., install Recloser Controller within 30' of Reclosers
4. If CSP Transformers are not available, call out VG1.5R
5. Item 1 shall be bonded to system ground.
6. Install pipe straps every 5 feet.

**Vacuum Interrupter Recloser
(CUTOUT MOUNT)
3-PHASE PRIMARY 24.9/14.4kV**

RUS
1/27/2025
REV. 0



VR3.3