



ITEM	PART #	MATERIAL	QTY	ITEM	PART #	MATERIAL	QTY
c	9373	Machine Bolt 5/8" req'd Length	4	av	3114	#2 Insulated Tap Wire	20'
d1	9091-2 $\frac{1}{4}$ "	Washer, square 2 1/4"	2	be	7180	Recloser, Oil Circuit (14.4 kV)	1
d2	9093	Washer, Curved, 3"x 3"x 11/16"	2	ek	9096	5/8" Lock Nut	4
p	9027	Crimpet #6 (connector)	2	fi	2147	Hot Line Stirrup #4 -4/0	4
ae	80	Arrester, Surge (18 kV)	2	rp1	4720	Arrester Bird Guard	2
af	4150	Cutout, Distribution, Open (27kV)	1	rp2	4730	Cut Out Cover Bird Guard	1
aj	3010	# 6 UV Jacket Green Stranded Copper	5'	rp3	4705	Bushing Covers	2
ap	2140	Connector, Hot Line Small	4	rp4	9340	Fiberglass Bracket 18"	1

NOTE:
 1. The recloser terminal bushing connected to the coil should be connected to the source.
 2. Recloser bushing covers are to only cover first skirt on each bushing.

**OIL CIRCUIT RECLOSER
 (WITH BYPASS CUTOUT)
 1-PHASE PRIMARY 24.9/14.4 kV**

RUS
 7/17/17
 Rev. C



VR1.2R